

WKC-3000

PTZ Controller



- Mini size PTZ controller
- IR On / OFF Button
- Fan & Heater ON/OFF function
- 3-Axis Joystick control of PTZ functions
- Preset position control (4 postions)
- Multiple protocol supported in each channel (Pelco D, WONWOO)
- Slave Keyboard support.




SPECIFICATIONS

MODEL	WKC-3000
Keyboard Communication	Interface : RS-485 / RS-422
	Operating distance : 4000ft (1.2km) on 24 AWG wire
	Protocol : Multiple (Pelco-D, DRX-502)
Connector Type Data	RJ-11 6-pin modular jack
Keyboard Button	5 PC Keyboard buttons
	Camera function button(F1, F2, Focus Far/Near), Menu button
Joystick	Pan / Tilt zoom control, variable speed control
Input Voltage	DC 12V ±2V
Power Consumption	Max. 140mA
Operating Temperature	0°C ~ 45°C
Humidity	10% ~70% Non-condensing
Dimension	130(W) x 125(H) x 145(D) mm
Weight	0.5kg



FUNCTIONS



1. Shows the communication status (Power, communication)
2. F1 : Tour Functional keys.
3. F2 : Pattern Functional keys.
4. 5. Near/Far Focus : used for setting Zoom camera focus.
6. Menu : Get into the dome menu (Press for 2 seconds)
7. Joystick : Control Pan, Tilt and Zoom In , Out
8. Joystick Button : Used to define the Presets



- Camera IR LED ON / OFF Control
IR On / OFF Switch
- Press Joystick Button and F1
White LED On / OFF Switch
- Press Joystick Button and F1
* On : Tele
* OFF : wide
For Auto setting Press Joystick button and F2

1. Communication Port : connect to PTZ port (cable).
2. Setting Switch : It used for setting address, bps and protocol setting.



- Tx Termination** ON/OFF
- Rx Termination** ON/OFF
- Baud Rates**
2400 (BPS) : SW7(OFF), SW8(OFF)
4800 (BPS) : SW7(ON), SW8(OFF)
9600 (BPS) : SW7(OFF), SW8(ON)
19200 (BPS) : SW7(ON), SW8(ON)



DIMENSIONS | Unit : mm

